

### *Amendments to the Claims*

This listing of claims will replace all prior versions and listings of claims in the application.

Claim 1 (currently amended): A method of efficiently processing a discrete time input signal having a plurality of input signal samples that occur at a first clock rate into a discrete time output signal having a second clock rate that is  $R$  times the first clock rate, the method comprising the steps of:

receiving the input signal; and

filtering the input signal with an  $N$ -taps finite impulse response (FIR) filter having  $N$  filter coefficients according to

$$\sum_{i=k}^{\text{ceil}[(N+1-k)/R]-1} b_{iR-k} u((m-i+k)T_s)$$

wherein  $b_{iR-k}$  is one of the  $N$  filter coefficients, ~~and~~  $u((m-i+k)T_s)$  is one of the input signal samples,  $T_s$  is a slow clock sampling period,  $m$  equals (0, 1, 2, 3, ...), and  $k$  equals (0, 1, 2, ...,  $R-1$ ).

Claim 2 (original): The method of claim 1, wherein the input signal is a position signal.

Claim 3 (original): The method of claim 1, wherein each of the  $N$  filter coefficients is the result of a discrete convolution of a series of FIR filters.

Claim 4 (original): The method of claim 1, wherein the output signal is sent to a control system that controls a photolithography scanning operation.

Claim 5 (currently amended): A system for efficiently processing a discrete time input signal having a plurality of input signal samples that occur at a first clock rate into a discrete time output signal having a second clock rate that is  $R$  times the first clock rate, the system comprising:

means for receiving the input signal; and

means for filtering the input signal with an  $N$ -taps finite impulse response (FIR) filter having  $N$  filter coefficients according to

$$\sum_{i=k}^{\text{ceil}[(N+1-k)/R]-1} b_{iR-k} u((m-i+k)T_s)$$

wherein  $b_{iR-k}$  is one of the  $N$  filter coefficients, ~~and~~  $u((m-i+k)T_s)$  is one of the input signal samples,  $T_s$  is a slow clock sampling period,  $m$  equals (0, 1, 2, 3, ...), and  $k$  equals (0, 1, 2, ...,  $R-1$ ).

Claim 6 (original): The system of claim 5, wherein the input signal is a position signal.

Claim 7 (original): The system of claim 5, wherein each of the  $N$  filter coefficients is the result of a discrete convolution of a series of FIR filters.

Claim 8 (original): The system of claim 5, wherein the output signal is sent to a control system that controls a photolithography scanning operation.